

4K Transmitter with AES67 Audio (LPCM up to 8CH)



Send and Receive up to 8-Channels.

Our newest 3G Ultra AES767 Transmitter features a HDMI loopout that supports AES67 audio systems/ integration with any Just Add Power AV distribution system. Mix and match the 3G Ultra 767AES Transmitter with ANY 3G Ultra or 2G Omega devices for interoperability with leading audio-over-IP technologies.


Features

Audio	Input LPCM audio up to 8 channels	Integrated Endpoint Control	Control endpoints with RS232, IR, and CEC	
	AES67 audio send and receive up to 8 channels		Image Pull	Preview an image from any source or display in any web browser or control system - up to 10 fps
	Inject AES67 audio into the J+P network			Scalability
HDMI	HDMI pass-through			

3G ULTRA VBS-HDIP-767AES


Just Add
Power
AV over IP Solutions

Front of Device:



All measurements in millimeters (mm)

Back of Device:



All measurements in millimeters (mm)

Specifications

Bandwidth	180-500 Mbps	POE	IEEE 802.3af (15.4W)
Compliance	HDCP 2.2 RoHS/FCC/CE	Ports	Gigabit Ethernet HDMI In HDMI Out 3-pin Euroblock RS232 3-pin Euroblock Stereo Out AES67 Gigabit Ethernet
Dimensions & Weight	184 x 30 x 152 mm 7.2" x 1.2" x 6.0" inch 0.45kg / 1.0 lb	Power Supply (not included)	5V-18V 5.5mm/2.1mm, Positive tip
Encryption	AES-128 Encryption	Supported Resolutions	Up to 4096x2160 (interlaced & progressive)
Operating Temp	0-60 °C / 32-140 °F		