

3G ULTRA VBS-HDIP-767DSS

Just Add
Power
AV over IP Solutions

4K Transmitter with Dante and AES67 Audio (LPCM up to 8CH)

The 3G Ultra 767DSS Dante® Sound System Transmitter adds compatibility with Dante® and AES67 audio networks to the any Just Add Power video distribution system.

Mix-and-match the 3G Ultra 767DSS Transmitter with any 3G Ultra and 2G Omega devices.

AES67 compatibility for interoperability with other leading audio-over-IP technologies.



Input and Extract up to 8 Channels from the Dante® network


Features

Audio	Input LPCM audio up to 8 channels	Integrated Endpoint Control	Control endpoints with RS232, IR, and CEC
	Dante® audio send and receive up to 8 channels		
	Inject Dante® audio into the J+P network	Image Pull	Preview an image from any source or display in any web browser or control system - up to 10 fps
HDMI	HDMI pass-through	Scalability	Fully compatible with all 3G Ultra and 2G Omega products

3G ULTRA VBS-HDIP-767DSS


Just Add
Power
AV over IP Solutions

Front of Device:



All measurements in millimeters (mm)

Back of Device:



All measurements in millimeters (mm)

Specifications

Bandwidth	180-500 Mbps	POE	IEEE 802.3af (15.4W)
Compliance	HDCP 2.2 RoHS/FCC/CE	Ports	Gigabit Ethernet HDMI In HDMI Out 3.5mm RS232 w/null modem Dante Gigabit Ethernet
Dimensions & Weight	184 x 30 x 152 mm 7.2" x 1.2" x 6.0" inch 0.45kg / 1.0 lb	Power Supply (not included)	5V-18V 5.5mm/2.1mm, positive tip
Encryption	AES-128 Encryption	Supported Resolutions	Up to 4096x2160 (interlaced & progressive)
Operating Temp	0-60 °C / 32-140 °F		